

Exita Swing 3-860-45lm SC WH



Product information "Exita Swing 3-860-45lm SC WH"

LED emergency exit light

Litegear Exita Swing: single-battery emergency light for escape route marking. Universal swivel mounting kit for wall and ceiling mounting. The luminaire can be used on one or two sides. Optionally, a mounting arm for side installation is available (see accessories). Flat, elegant acrylic LED pictogram surface. Over 60% power saving compared to conventional 8W versions with fluorescent tubes. The exit sign sheets are interchangeable and are fastened by push-button fasteners. Manual test function and green status LED display. Continuous operation via 230V mains voltage or battery emergency operation of up to 3 hours. Fast installation and easy battery change. Almost no maintenance cost due to LED technology! 3x pictograms for escape Arrow: "left/right/up" included.

Optionally, we offer additional escape route pictograms in a set.

- Material: polycarbonate and acrylic
- incl. 4 legends
- Swivel range: 90°
- Accupack included
- average battery life: 4 years max.
- viewing distance: 24 meters
- Overload and discharge protection
- Discharge current: 160mA
- Battery: 4,8v 600mA, NI-CD
- charging current: 30mA



Technical Details:

Luminous Flux	45 lm
Light Yield:	15 lm/W
Light Temperature:	6000 K
Color Rendering Index (CRI)	≥80 Ra
Color Consistency (SDCM):	6
Power Consumption:	3 W
Power Factor (PF):	0.5
Operating Hours:	>50.000 h L70/B50
Switching Cycles:	>30.000
Ignition Time:	<1 s
Ambient Temperature (TA):	0°C - 40°C
Housing Material:	Polycarbonat
Housing Color	white
Pivot Range tilt:	90 °
Net Weight:	939 g
Warranty	3 years

Information and Downloads:

