## LITEGEAR LED Lighting Solutions

## JUPITA Motion HF Sensor





## **Product information "JUPITA Motion HF Sensor"**

motion sensor for Litegear Jupita Highbay

**Detail Information** 

Mounting Height: 15m Max

DC Input Voltage:12/24V DC &plusm;1V

Rated Voltage:12/24V
Stand-by Power:< 0.3W
Working Mode:0-10V DC
Operating Temperature:-35°C°C
Lifetime: 50,000h @ Ta Full Load

Detecting Angle:150°(wall Mounting) 360°(ceiling Mounting)
High Light: microwave movement sensor, dimmable motion sensor

Product Description: MC079D RC 2

**Daylight Priority Function** 

DC Operation Sensor, 12/24V DC Input High Bay Sensor for Warehouse

1. Features

- 12/24V DC input, for DC systems or LED power supplies with 12/24V DC auxiliary power output
- 0-10V dimming port, 3 or 2 step dimming function
- Newly patent design sensor antenna with two detection mode: high sensitivity detection and interference immunity detection. (suitable for installation environments with many metal reflective surfaces)
- Compact design, special for industrial lamps, sensors can be fixed at the edg or center of UFO.
- 15m maximum installation height, suitable for most warehouses
- Patented remote control, transmitting angle of the remote control is adjustable according to mounting height
- Override function
- Dim+/Dim- to set occupancy light level
- Daylight priority function







## **Technical Details:**

Housing Material:	plastic
Housing Color	white
Warranty	5 years

Information and Downloads:

