

Casambi Smart Wireless auf 0-10V/Dali Dimmer Ausgang Adapter



Product information "Casambi Smart Wireless auf 0-10V/Dali Dimmer Ausgang Adapter"

Smart wireless bluetooth mesh receiver

- wireless receiver with analogue 0-10V dimmer output 1 channel
- compact dimensions for installation in boxes and lights

Wireless control unit for 0/1-10V LED drivers

With the help of the innovative Bluetooth 4.0 control unit IBTU Casambi Adapter, you can control 1/0-10V LED drivers via smartphone, tablet, but also via the normal switch.

The CASAMBI compatible module is based on a very small, IP20-protected housing with a height of 22.3 mm and a total length of 56.5 mm and can be installed in wallboxes or luminaires. The module is equipped with a configurable interface (max. 7mA control current) for connecting dimmable electronic 0/1-10V LED driver.

Light scenes can be selected and the switch-on light level can be set using a mains switch. As soon as you have installed the devices in your 0/1-10V light and combined them into a network using your free Casambi app (Android + iOS), the devices form a continuous mesh with each other based on the far-reaching and energy-saving standards Bluetooth 4.0. As soon as only one lamp is nearby, you can control all lamps. You don't need a central controller nearby.

A variety of control options are available to you via the app - for example the overall light, but also individual lights in the network or just "lights nearby" on and off with a click, dim the light, combine



Technical Details:

Ambient Temperature (TA):	-20°C - 45°C
Housing Material:	plastic
Housing Color	white
Channels:	1
Dimming:	1-100%
Dimensions	49,5x35,8x22,6 mm
Warranty	2 years

Information and Downloads:



app, the light turns on.

You can find the free Casambi App in the App or Plasy Store.

iOS / Apple / iPhone / iPad

iOS/AppleWatch

Android