Product Information

Order number: LG31319END

Xona Maxima Basic END TRUNKING RAIL 1U-150 END Unit









Technical Details:

Housing Material:	steel
Housing Color	white
Dimensions	1499x69x41 mm
Net Weight:	1752 g

Information and Downloads:

Product information "Xona Maxima Basic END TRUNKING RAIL 1U-150 END Unit"

Mounting rail for Maxima Basic LED module or luminaire support module
End unit with out cennection fork

The trunking rail is a support profile with a 5-, 8- or 12-wire internal wiring. By means of integrated connectors and mechanical fork connection, several profiles can be connected without tools in a very short time.
Via vertical connectors, the luminaire modules are supplied with control signals and 230V power. Each luminaire module can be individually powered by one of the three internal 230V phases via a phase selector so that different lighting zones can be created or in daytime operation the luminous intensity can be adapted to the daylight conditions and avoid unnecessary electricity costs. The assignment of the individual wires can be found in our Maxima Basic brochure.

- End piece without fork connector.
- Only fits for end caps, not for end box.
- Cannot be extended with additional mounting rails!

Litegear GmbH
An Fürthenrode 45
52511 Geilenkirchen

Tel.: +49 (0)2451 48453-0
Fax: +49 (0)2451 48453-13
www.litegear.de