

# Ekova SELECT Plug and Play Sensor 12V DC 30mA IP20



## Product information "Ekova SELECT Plug and Play Sensor 12V DC 30mA IP20"

Motion detector for Ekova Select series

- Microwave motion radar detector
- Plug and Play accessory kit
- Can be installed easily even afterwards by a technician
- Power supply low voltage by connection to LED driver
- Set up via optional remote or DIP switch

### Technical datas:

- Detection area: max. 9m @2m height, max. height 4m, 50%/100% switch, ceiling 360°, wall 150°
- Frequency: 5,8GHz +/-75Hz

Operational voltage: 7,5-12V DC 30mA

operational power consumption: 0,3W

Dimming methode: PWM: Dimmlevel: 0%/20% im Standby for 15min/∞


Stand by Time 100% brightness: 5s, 1Min. 3 Min. 10 Min.

Daylight thershold: 30 Lux or disable

### Applications:

hallway, sanitary areas, warehouse, loading area, cold storage

optional remote controller for easy set up available



### Technical Details:

Ambient Temperature (TA):	-20°C - 60°C
Housing Material:	plastic
Housing Color	white
Dimensions	52x16x16 mm
Warranty	3 years

### Information and Downloads:

