

Ekova SELECT Plug and Play Sensor 12V DC 30mA IP20



Product information "Ekova SELECT Plug and Play Sensor 12V DC 30mA IP20"

Motion detector for Ekova Select series with orientation light

- Microwave motion radar detector
- Plug and Play accessory kit
- Can be installed easily even afterwards by a technician
- Power supply low voltage by connection to LED driver
- Set up via optional remote or DIP switch

Technical datas:

- Detection area: max. 9m @2m height, max. height 4m, 50%/100% switch, ceiling 360°, wall 150°
- Frequency: 5,8GHz +/-75Hz

Operational voltage: 7,5-12V DC 30mA

operational power consumption: 0,3W

Dimming methode: PWM: Dimmlevel: 0%, 10%, 20%, 30% im Standby for 5min to ∞

Stand by Time 100% brightness: 5s, 1Min. 3 Min. 10 Min.

Daylight thershold: 30 Lux or disable

Applications:

hallway, sanitary areas, warehouse, loading area, cold storage

optional remote controller for easy set up available



Technical Details:

Ambient Temperature (TA): -20°C - 60°C

Housing Material: plastic

Housing Color: white

Dimensions: 52x16x16 mm

Net Weight: 10 g

Warranty: 3 years

Information and Downloads:

