

# Xona Maxima Basic TRUNKING RAIL 2U-300



## Product information "Xona Maxima Basic TRUNKING RAIL 2U-300"

Mounting rail for Maxima Basic LED module or luminaire support module

The trunking rail is a support profile with a 5-, 8- or 12-wire internal wiring. By means of integrated connectors and mechanical fork connection, several profiles can be connected without tools in a very short time.

Via vertical connectors, the luminaire modules are supplied with control signals and 230V power. Each luminaire module can be individually powered by one of the three internal 230V phases via a phase selector so that different lighting zones can be created or in daytime operation the luminous intensity can be adapted to the daylight conditions and avoid unnecessary electricity costs. The assignment of the individual wires can be found in our Maxima Basic brochure.



### Technical Details:

|                   |               |
|-------------------|---------------|
| Housing Material: | steel         |
| Housing Color     | white         |
| Coating:          | lacquered     |
| Dimensions        | 2999x69x41 mm |
| Net Weight:       | 2970 g        |
| Warranty          | 5 years       |

Information and Downloads:

