

Wireless Bluetooth Mesh 2,4GHz Zhaga Book Integrated DIM Sensor ANT4E-6, IP67



Product information "Wireless Bluetooth Mesh 2,4GHz Zhaga Book Integrated DIM Sensor ANT4E-6, IP67"

Meshle PIR Motion Sensor with wireless Bluetooth Mesh 2,4GHz for CUPower Sky driver

IP65 PIR motion sensor for LED luminaires.
 Recessed integration in false ceilings or housings in-/outdoor
 Zhaga Book Schnittstelle zum Treiber

Perfect for the following applications:

- work spaces, warehouse
 - WCs, walkways
 - factory, office
-
- Operation technology: PIR sensor
 - Swarm Function within Mesh
 - Montagehöhe: 2m bis 3,6m
 - Detection range: max. 4-8m
 - Detection angle: 360° ceiling-
 - Hold time: adjustable via App
 - Daylight threshold: adjustable via App
 - Standby power: 0,5W
 - Zhaga Dimming connector 3,3V DC >50mA
 - Protocol: Meshle
 - Supports UART-based communication with CUPower Sky drivers
 - Steuerung via App

other details refer to datasheet.



Technical Details:

Power Consumption:	1 W
Operating Hours:	>40.000 h
Switching Cycles:	>25.000
Ambient Temperature (TA):	-20°C - 60°C
Housing Material:	plastic
Housing Color	white
Dimensions	31x38 mm
Cut-Out Dimensions	20,4 mm
Warranty	5 years

Information and Downloads:

